



## Art.no.: 13138-402



## Notor 78

50/50, Start/Single, DALI/Phase-pulse

### DESIGN

<b>Louvre</b> Delta	<b>Length, mm</b> 1174
<b>Colour</b> White	<b>Width, mm</b> 78
<b>RAL</b> 9016	<b>Height, mm</b> 78
<b>Weight, kg</b> 4.6	<b>Module</b> 1200

### TECHNICAL DATA

<b>Installation</b> Start/Single	<b>IP rating</b> 20
<b>Protection class</b> 1	<b>Light control</b> DALI/Phase-pulse

### ELECTRICAL DATA

**Effect, W** 37

### LIGHTING DATA

<b>Light distribution</b> 50/50	<b>LED driver, h/max failure %</b> 100 000/10 %
<b>Lumen output</b> 4432	<b>SDCM</b> 3
<b>lm/W</b> 120	<b>CRI</b> 80
<b>Lumen maintenance L90 B10, h</b> 50 000	<b>CCT, K</b> 3000
<b>Lumen maintenance at 50 000 h</b> 0,92	<b>Light source</b> LED

**A suspended workplace luminaire that produces direct/indirect light. Delta louvres provide high efficiency and optimal lighting comfort. Single or continuous installation.**

**Installation** Designed for single or continuous installation via a wire pendent and special loops that give flexible c-c spacing. Special loops included in the delivery. Wires suspension are ordered separately. Can also be wall mounted with special bracket, see Accessories.

**Connection** The start luminaire is supplied with 2,4 m mains cable excluding plug as standard. With additional numbers -448, -449 and -474 is the luminaire equipped with 2,4 mains cable, 3x1,0 mm<sup>2</sup> and earthed plug. The connecting mains cable comes out on the same side as the pull switch. The luminaire unit is equipped with a through-wiring cable (5x1.5 mm<sup>2</sup>) and a snap-in connection in each end cap. In a continuous installation, the luminaire row should always begin with a start luminaire.

**Design** Body in white (RAL 9016) or natural anodised, extruded aluminium finish. Direct/indirect: the top is covered by an active film which generates a broad light pattern and which works as a dust cover.

**Louvre** Delta – microprism louvre in acrylic (PMMA).

**Reflector** The louvres act as reflectors.

**Dimming** DALI/phase-pulse control as standard. Luminaires with DALI/phase pulse control have CLO (Constant Light Output) as standard. Additional number -448, -449 and -474 is only available with single installation.

30/70, 70/30 contains 2 DALI drivers (requires 2 DALI addresses).

50/50 and Direct light distribution contains 1 DALI driver.

e-Sense Active – PIR sensor with presence and daylight control via DALI.

**Miscellaneous** CLO (Constant Light Output) maintains the correct light from the luminaire for the duration of its rated life.

To calculate how many luminaires and accessories you will need to complete a run, please use our

For exact lengths, please refer to the dimension drawing.